

CorePro LEDtube Universal HO - 600 mm

Ballast Compatibility



KEY

	Ballast is compatible
*	Ballast is compatible, light output may differ >10% compared to specifications
	Ballast is not compatible
	Ballast LEDtube combination not tested

This document is for information purposes and must be treated as recommendation. Philips attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions



			CorePro LEDtube UN 600mm HF 900lm
			Model number / EOC code: 9290024198 / 8718699782771 9290024199 / 8718699782795 9290024200 / 8718699782818
			AC (50Hz) on HF Ballast Compatible
PHILIPS	Ballast type	10nc / Ref. no.	Lamps on ballast
	HF-P 118 TLD III IDC	9137130312	1
	HF-P 218 TLD III IDC	9137130313	2
	HF-S 118 TLD II	9137130320	1
	HF-S 218 TLD II 220-240V 50/60Hz	9137130323	2
	HF-S 3/4x18 TLD II	9137130326	3
	HF-S 3/4x18 TLD II	9137130326	4
	HF-Matchbox 1x18 Blue	9137004180 / 9137004179	1
	HF-Matchbox 1x18 RED	9137004234	1
	HF-P 3/4x18 TLD III IDC	9137130314	3
OSRAM	QTP8 1x18		1
	QTP8 2x18		2
	QT-FIT8 1x18		1
	QT-FIT8 2x18		2
	QT Fit 5/8 1x18-39		1
	QTP-OPTIMAL 118-40		1
	QTP-OPTIMAL 218-40		2
	QT Fit 5/8 2x18-39		2
	QT-FIT8 3/4x18		3
HELVAR	EL1x18ngn		1
	EL2x18ngn		2
	EL 3/4x18ngn		3
	EL 3/4x18ngn		4
	EL1x18s		1
	EL 4x18ngn		4
TRIDONIC-ATCO	PC 118 PRO Ip	22185213	1
	PC 218 PRO Ip	22185216	2
	PC 1X18-24W BASIC	22176000	1
	PC 1x18 T8 TOP sl	22185222	1
	PC 3/4X18 TOP Ip	22185219 / 22185228	3
	PC 3/4X18 TOP Ip	22185219 / 22185228	4
	PC 1/14-35/24/39 T5 PRO-M Ip	22176182	1
	PC 2/14-35/24/39 T5 PRO-M Ip	22176185	2
	PC 1x18 T8 TEC	87500113	1
VOSSLOH-SCHWABE	PC 2x18 T8 TEC	87500114	2
	ELXc 136.200	188314	1
	ELXc 236.208		2
	ELXc 424.379	188116	3
	ELXc 424.379	188116	4
	ELXc 418.204	188318	3
	ELXc 418.204	188318	4
BAG-HUECO	ELXc 136.207		1
	BCS18.1FX-11/220-240	10077588	1
	BCS18.2FX-11/220-240	10077589	2
	BCS18.3-4LR-01/220-240 3lamp	10050999	3
Others	BCS18.3-4LR-01/220-240 4lamp	10050999	4
	Direct mains		
	Electro Magnetic Ballast		

General notes Philips CorePro LEDtube Universal HO

General notes: Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.

Please note that Philips LEDtubes are only tested with HF ballast on AC operation. The performance of Philips LEDtubes on HF ballasts with DC operation is not tested and is therefore not guaranteed. Philips LED tube InstantFit range is designed to work on HF ballasts only. For EM ballasts or direct mains connection, please contact a Philips sales representative for more information on our EM/Mains compatible range. This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips LEDtubes with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips LEDtube. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on www.philips.com/ledtube