

Philips CorePro LED PLC 4.5W 8xx 4P G24q-1



Ballast Compatibility

KEY

	Ballast is compatible
	Ballast is compatible, light output may differ >10% compared to specifications
	Ballast is compatible and conditional released for dimming
	Ballast is not compatible

This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions

			Philips CorePro LED PLC 4.5W 8xx 4P G24q-1	
			Model number / EOC code: 9290013510 / 871869670663300 9290013511 / 871869670665700	
			AC (50Hz) on HF Ballast Compatible	
	Ballast type	10nc	Lamps on ballast	
PHILIPS	HF-M 113 TL/PLS/PLC SH	9137004137	1	
	HF-M 113 TL/PLS/PLC LH	9137004139	1	
	BLUE 114 LH TL/PLS/PLC	9137004217	1	
	RED 114 SH TL/TL5/PLC/S	9137004232	1	
	HF-P 113-17 PL-T/C/R EII	9137006311	1	
	HF-P 2 113-17 PL-T/C/R EII	9137006312	2	
	EB-C 113 PL-T/C 220	9137131984	1	
	EB-C 213 PL-T/C 220	9137131985	2	
OSRAM	QT-ECO 1X4-16/220-240 L		1	
	QT-ECO 1X4-16/220-240 S		1	
	QTP-D/E 1X10-13		1	
	QTP-D/E 2X10-13		2	
VOSSLOH-SCHWABE	ELXc 213.870 188698	188698	2	
	ELXc 213.870 188698	188698	1	
	ELXs 121.901 188663	188663	1	
	ELXs 121.904 188664	188664	1	
TRIDONIC	PCA 1x11/13 TC EXCEL one4all	22185134	1	
	PCA 1x11/13 TC ECO	22185126	1	
	PCA 2x11/13 TC EXCEL one4all	22185135	2	
	PCA 2x11/13 TC ECO	22185127	2	
	PC 1x5-16W BASIC	24138830	1	
	PC 1x5-16W BASIC sl	24138833	1	
	PC 1/2x9-13 TC PRO	22176405	2	
BAG HUECO	BCD131-2Q-01/220-240/1-10V	10096393	2	
	BCD131-2Q-01/220-240/1-10V	10096393	1	
	BGS211-2LS-01/220-240	10095043	2	
	BGS211-2LS-01/220-240	10095043	1	
	BGS211-2Q-01/220-240	10097543	2	
	BGS211-2Q-01/220-240	10097543	1	
	BGS211-2Q1-01/220-240	10095743	2	
	BGS211-2Q1-01/220-240	10095743	1	
	EBS211C-01/220-240	10050990	1	
	EBS211M-01/220-240	10050994	1	
	EBS16.1C-01/220-240	10050989	1	
TCL	BCC 121	137946HTC	1	
	BCC 121/2	137969/21MM	1	
	BCC 121/2 SL	137944/21H	1	
	BCC 121 SL	137944B/21H	1	
	BCC 121 P54	137969P21MM	1	
	MBQ 113/2	137968/113	1	
	MB213	137988/213	2	
	MB213/2	137988/2132	2	
MBQ 213/2	37968/213	2		

General note Philips CorePro LED PLC

General notes: Refer to the product reference number in the header of the columns to use this product-ballast compatibility list. Please note that Philips CorePro LED PLC 4P are only tested with HF ballast on AC operation. The performance of Philips CorePro LED PLC 4P on HF ballasts with DC operation is not tested and is therefore not guaranteed. Philips CorePro LED PLC 4P range is designed to work on HF ballasts only. For EM ballasts configuration, please contact a Philips sales representative for more information on our EM compatible range. This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips CorePro LED PLC 4P with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips CorePro LED PLC 4P. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on www.philips.com/ledtube

Dimming: Philips CorePro LED PLC 4P are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply